

DESCRIPTION

The ER-604W is a compact, lightweight shoulder-type megaphone with whistle signal. Its close-talking microphone has a handy-to-operate volume control and press-to-talk switch. External microphone inputs on the unit's rear panel can accept an optional microphone or a headset microphone for hands-free use. In addition, an AUX (auxiliary) input can accept a CD, MD, or cassette player.

SPECIFICATIONS

* 0 dB = 1 V

Power Source	R6 battery × 8 (12 V DC) 12 V DC/0.8 A or more (AC adapter or DC power supply unit usable)
Rated Output	6 W
Maximum Output	10 W
Battery Life	Voice: Approx. 10 hours (R6P manganese dioxide battery use) Whistle: Approx. 30 minutes (continuous use)
Audible Range	Voice: 160 m (under noise level of 55 dB) Whistle: 160 m (under noise level of 55 dB)
Microphone	Close-talking type, press-to-talk switch, volume control Fixed to the microphone hanger on the unit's top panel
Signal	Whistle, push switch activation
Input	MIC 1: -40 dB*, 1.5 kΩ, Ø6.3 phone jack MIC 2: -18 dB*, 3 kΩ, Ø3.5 mini jack, phantom powering AUX (auxiliary): -12 dB*, 18 kΩ, Ø3.5 mini jack External power supply: 12 V DC Note: MIC1, 2, and AUX inputs can be used at the same time. However, their individual volume cannot be adjusted as the unit's volume control is common to those inputs.
Other Function	Voice switch (functions to activate the unit with external input signals, and to make the unit in stand-by status with no external signal.) Battery check
Finish	Body, microphone: ABS resin, off-white Shoulder pad, belt: Black
Dimensions	102 (W) × 258 (H) × 216 (D) mm (excluding shoulder belt)
Weight	1.6 kg (without batteries)
Accessory	Ø3.5 mini plug×1, External power supply cord (1 m)×1
Option	Headset microphone: WH-4000A, WH-4000H Dynamic microphone: DM series Speaker stand: ST-16A

Notes

- Batteries are optional.
- Do not use the battery from a starting car as its voltage is high. Otherwise, the megaphone may fail.
- Battery Life assumes that the megaphone is used for 30 minutes a day.
- Audible Range assumes that the megaphone employs new batteries and is used on a quiet street.
It varies depending on such conditions as battery consumption, ambient noise, wind direction and obstacles.

APPEARANCE

