


FLUSH CEILING MOUNTING BRACKET

C-BC511U C-BC511U-S

Thank you for purchasing TOA flush ceiling mounting bracket.
Please carefully follow the instructions in this manual to ensure long, trouble-free use of your equipment.



1. SAFETY PRECAUTIONS

- Before installation or use, be sure to carefully read all the instructions in this section for correct and safe operation.
- Be sure to follow all the precautionary instructions in this section, which contain important warnings and/or cautions regarding safety.
- Keep this instructions handy for future reference.



WARNING

Indicates a potentially hazardous situation which, if mishandled, could result in death or serious personal injury.

- Avoid installing the unit in unstable locations, such as on a rickety or slanted surface. Failure to do so may result in the unit falling and possibly causing personal injury.
- Install the unit only in a location that can structurally support the weight of the unit and the mounting bracket. Doing otherwise may result in the unit falling down and causing personal injury and/or property damage.
- Do not use the bracket for mounting any camera other than the combination camera. Failure to follow this instruction could cause the camera to fall and result in personal injury.
- Ensure that all screws and fixing mechanism are securely tightened. If they are not tightened or firmly secured after installation, the unit could fall down, possibly resulting in personal injury.

When Installing the Unit

- Do not use any methods other than specified to mount the bracket. Extreme force is applied to the unit and the unit could fall off, possibly resulting in personal injuries.
- Attach the safety wire to the unit. If not attached, the unit could fall off, resulting in personal injury.
- Use nuts and bolts that are appropriate for the ceiling's or wall's structure and composition. Failure to do so may cause the unit to fall, resulting in material damage and possible personal injury.
- Tighten each nut and bolt securely. Ensure that the bracket has no loose joints after installation to prevent accidents that could result in personal injury.
- Avoid installing the unit in locations exposed to sea breeze or corrosive gas. Mounts may become corroded, eventually causing the unit to fall off, which could result in personal injury.
- Do not mount the unit in locations exposed to constant vibration. The mounting screws and/or bolts may be loosened by excessive vibration, potentially causing the unit to fall, which could result in personal injury.



Indicates a potentially hazardous situation which, if mishandled, could result in moderate or minor personal injury, and/or property damage.

When Installing the Unit

- To avoid electric shock, be sure to switch off the power before power supply wiring work.
- Leave the installation of the unit to your TOA dealer because the installation requires expert experience and skills. Incorrect installation may cause an electric shock or personal injury.
- Avoid touching the unit's sharp metal edge to prevent injury.

When the Unit is in Use

- Do not stand or sit on, nor hang down from the unit as this may cause it to fall down or drop, resulting in personal injury and/or property damage.
- Be sure to inspect the unit periodically for safety use. Damage or corrosion of the mounting bracket may cause dropping of the unit, resulting in personal injury and/or property damage. Contact your TOA dealer as to the periodical inspection.

2. GENERAL DESCRIPTION

The mounting bracket is designed to be used for mounting the Combination Camera (C-CC514, C-CC564 and C-CC574) and/or Network Combination Dome Camera (N-CC2564) in a ceiling. It can reduce the camera's exposed area and is ideal for mounting cameras to gypsum board ceilings or other weak ceiling panel materials in which mounting screws cannot be securely inserted. Two types of mounting bracket are available: the C-BC511U (transparent dome version) and C-BC511U-S (smoked dome version).


Since camera orientation cannot be seen from outside the enclosure when the C-BC511U-S is used, it is more effective in enhancing the effect of surveillance.

3. HANDLING PRECAUTIONS

- Do not install the unit in locations exposed to constant vibration. Since the unit is not designed for vehicle or ship use, do not install it in a vehicle or ship.
- To prevent the unit falls off, be sure to hang the safety wire first when installing the unit.
- Do not give the unit a great shocks or vibration, as the unit may fall off and cause damage.
- The Combination Camera is solely designed for suspended installation. The dome of the mounting bracket must be mounted facing down and perpendicular to a horizontal ceiling surface. Take special care not to install the dome at a tilted angle.
- Fix the camera to the bracket using the designated mounting screws, and ensure that they are securely mounted without any play.
- Use the unit whenever the space between suspended ceiling panel and upper ceiling exceeds a height of 250 mm (9.8 inch).
- The ceiling panel to which the unit will be mounted must be no more than 40 mm (1.6 inch) in thickness.

4. INSTALLATION

[Main body mounting view]



Be sure to carefully read the installation manual supplied with the camera.


1. Attach the base unit to the flush ceiling mounting bracket.

Note

Use the camera mounting screws supplied with the combination camera when attaching the base unit.

2. Attach the flush ceiling mounting bracket equipped with the base unit to the flush ceiling mounting anchor bolt installed into the upper ceiling (ceiling behind the ceiling panel).
3. Connect cables and attach the camera unit to the base unit.
4. Align the bezel's positioning mark with that on the flush ceiling mounting bracket and insert the camera into the mounting bracket.
5. Rotate the bezel counterclockwise until it locks into place.

[Installation dimensional diagram]



5. SPECIFICATIONS

Finish	Bracket : Aluminum, black, paint Bezel : PC/ ABS resin, cool gray Dome cover : Acrylate resin, transparent (C-BC511U) : Acrylate resin, smoked (transmittance: approx. 20%) * (C-BC511U-S)
Dimensions	$\varnothing 250 \times 282.7$ (H) mm ($\varnothing 9.8 \times 11.1$ (H) inch) (dome external diameter : $\varnothing 125$ mm ($\varnothing 4.9$ inch))
Weight	1.2 kg (2.6 lb)
Applicable camera	C-CC514, C-CC564, C-CC574, N-CC2564

* When using the C-BC511U-S, the subject's illumination must at least be 5 times brighter than when using the C-BC511C.

Note: The design and specifications are subject to change without notice for improvement.

• Accessories

Safety wire 1 Pattern paper 1